

4 Shipment, unpacking

SIMOREG converters are packed in the production works according to the relevant ordering data. A product packing label is attached to the box.

Protect the package against severe jolts and shocks during shipment, e.g. when setting it down.

Carefully observe the information on the packaging relating to transportation, storage and proper handling.

The SIMOREG device can be installed after it has been unpacked and the shipment checked for completeness and/or damage.

The packaging materials consist of cardboard and corrugated paper and can be disposed of according to locally applicable waste disposal regulations.

If you discover that the converter has been damaged during shipment, please inform your shipping agent immediately.

4.1 Remove the transportation protection for devices with 1500A to 2000A rated DC

- ① Remove the brackets for cabinet mounting by cutting open the cable ties and fix them to the outside of the device if required.
- ② Remove the six M8 hexagon-head nuts.
- ③ Remove the two M8 hexagon-head nuts and the transportation bracket.
- ④ Remove the two banding strips.
- ⑤ Remove the transportation sheet after assembling the device and before startup by removing the six M6 hexagon-head nuts.



